

ROOM TEMPERATURE SENSOR TEHR NTC 10-C-P

Remote control unit TEHR NTC-10-C-P is made for detecting and controlling of the room temperature.

The sensor of the unit is connected to the sensor input of the controller and the set point is adjusted by the potentiometer for desired temperature.

The proper potentiometer (1...10 k Ω), resistors and possible accessories are to be specified on order.

Sensor resistance at different temperatures:

$^{\circ}\text{C}$	Ω	$^{\circ}\text{C}$	Ω
120	597	25	10 000
100	973	20	12 090
90	1266	15	14 690
80	1668	10	17 960
75	1924	5	22 050
70	2228	0	27 280
65	2588	-5	33 900
60	3020	-10	42 470
55	3536	-15	53 410
50	4160	-20	67 770
45	4911	-25	86 430
40	5827	-30	111 300
35	6940	-40	-
30	8313	-50	-



Technical data:

sensor	NTC 10-C, 10 k Ω at 25 $^{\circ}\text{C}$
range	0...+50 $^{\circ}\text{C}$
accuracy	± 0.25 $^{\circ}\text{C}$ at 25 $^{\circ}\text{C}$
housing	ABS plastic, IP20
mounting	on the wall or on the standard flush mounting box (60 mm hole distance)
dimension (w x h x d)	86 x 85 x 30 mm

Connection:

1	sensor
2	sensor
3	not in use
4	potentiometer -
5	potentiometer (output)
6	potentiometer +

Ordering guide:

Model	Product number	Description
TEHR NTC 10-C-P	117M230	room temperature sensor, NTC element
Options:		
TEHR-S	1170080	push button (no / nc) 24 Vac/dc
TEHR-S5	1170090	5-position switch
TEHR-L	1170100	LED-lamp (24 V)
TEHR-N	1171140	display

Products fulfill the requirements of directive 2004/108/EC and are in accordance with the standards EN61000-6-3: 2001 (Emission) and EN61000-6-2: 2001 (Immunity).